



SMX1200XLHG Estimatif Runtime

Load in Watts

UPS	Battery Pack	BP Qty	20W	40W	60W	80W	100W	120W	160W	200W	300W	400W	500W	600W	700W	740W
SMX1200XLHG	Internal Batteries	0	505	305	214	162	129	106	77	60	37	25	19	14	12	10
SMX1200XLHG	BP36V15-2U	1	1559	986	714	555	451	378	283	224	143	102	78	62	51	48
SMX1200XLHG	BP36V42-3U	1	3444	2264	1678	1328	1095	930	710	571	376	276	214	173	144	135
SMX1200XLHG	BP36V42-3U	2	5878	4022	3049	2450	2044	1751	1357	1104	744	555	436	357	301	283
SMX1200XLHG	BP36V42-3U	3	7856	5546	4279	3479	2927	2524	1975	1618	1105	832	659	543	460	433
SMX1200XLHG	BP36V42-3U	4	9493	6880	5389	4425	3750	3252	2564	2113	1457	1105	880	729	620	584
SMX1200XLHG	BP36V42-3U	5	10871	8058	6395	5297	4518	3937	3127	2590	1800	1372	1098	912	778	734
SMX1200XLHG	BP36V42-3U	6	12048	9104	7312	6105	5237	4584	3664	3048	2134	1635	1313	1094	935	883
SMX1200XLHG	BP36V42-3U	7	13063	10041	8150	6854	5912	5195	4177	3490	2460	1892	1524	1273	1090	1031
SMX1200XLHG	BP36V42-3U	8	13949	10884	8919	7552	6645	5774	4669	3915	2777	2144	1732	1449	1244	1177
SMX1200XLHG	BP36V42-3U	9	14728	11647	9628	8202	7142	6323	5139	4326	3086	2391	1936	1624	1396	1321
SMX1200XLHG	BP36V42-3U	10	15419	12341	10283	8810	7705	6844	5590	4722	3387	2634	2138	1796	1546	1464

All runtime values are in minutes